



**VIVAX**  
**METROTECH**

# 10-Watt Transmitter

## Loc3 Series Broadband Transmitter

- Built-in AVO meter
- Optional transmitter-to-receiver radio link
- SD mode for positive location in congested areas
- Lightweight - Only 7.15 lbs. / 3.24 kg with Li-ion battery
- AC/DC external power sources

**The Loc3 series 10-Watt broadband transmitter** has selectable induction and direct connection frequencies from 98Hz to 200kHz, SD mode (Signal Direction), fault find and true resistance measurement up to 1 Mohm. The two inch by one inch dot matrix display with LED backlight shows output current, connection type, volts, resistance, frequency, volume, battery condition and high voltage warnings.

The optional Transmitter Link (Tx-Link) installed in the receiver and transmitter, remote operation of the transmitter from the receiver is possible. The range of the radio transmitter link depends on having a clear "line of sight" between receiver and transmitter but is typically around 300m / 985 ft.

Signal Direction (SD) mode feature verifies if the line being located is the target that the transmitter is connected to. When a transmitter is connected to a target line, the signal travels along it and finds the easiest way to travel back, usually via the ground and ground stake. However, very often the signal will travel back along adjacent utilities which offer an easier route. As a result, there can be multiple signals radiating from utilities in the area making it difficult to identify the target line. These return signals are typically traveling in the opposite direction than the applied signal. The Signal Direction feature identifies which direction the signal is flowing and hence the target line.

Packaged in a lightweight, rugged, ergonomic IP54 housing, the transmitter provides consistent current output in direct connect, clamp or induction modes and protection against incoming voltages up to 240V.



	Loc3-10Tx Transmitter Specifications														
Construction	High impact ABS injection molded housing														
Weight and Dimensions	9.9lbs (4.4kg), 13.1in(L) x 7.2in(W) x 7.3in(H) (332mm x 182mm x 185mm)														
Display	2.4in x 1.3in (60mm x 32mm Monochrome-dot-matrix graphic LCD display with LED backlight														
Battery options	Supplied with 12 x D cell alkaline batteries Optional Li-ion rechargeable battery tray with charger														
Battery life	At 70°F (21°C) - continuous use (based on the battery type and quality) <table><tr><th>Output Power</th><th>Alkaline</th><th>Li-ion (Rechargeable)</th></tr><tr><td>1 watt</td><td>25 hours</td><td>50 hours</td></tr><tr><td>5 watt</td><td>6 hours</td><td>10 hours</td></tr><tr><td>10 watt</td><td>4 hours</td><td>6 hours</td></tr></table> Li-ion batteries will withstand 500 charging life cycles			Output Power	Alkaline	Li-ion (Rechargeable)	1 watt	25 hours	50 hours	5 watt	6 hours	10 hours	10 watt	4 hours	6 hours
Output Power	Alkaline	Li-ion (Rechargeable)													
1 watt	25 hours	50 hours													
5 watt	6 hours	10 hours													
10 watt	4 hours	6 hours													
Operating Frequencies	<b>Induction</b> - Available frequencies between 98Hz and 200kHz <b>Direct Connection</b> - Available frequencies between 98Hz and 200kHz <b>Clamp</b> - Frequencies between 8kHz to 131kHz														
Operating modes	<b>Induction mode</b> - applies signal inductively using internal antenna <b>Direct connection mode</b> - applies signal directly to the cable by clipping one output lead to the cable, the other to an independent ground <b>Clamp mode</b> - applies signal using an inductive clamp (aka toroid or coupler) that is placed around the target pipe or cable														
Output Protection	Output protected against accidental momentary connection to up to 240V AC														
Environmental	IP54 and NEMA 4														

## What's in the box



## Popular Accessories



Transmitter Link



Rechargeable battery



DC power lead



Clamps



Live Plug connector



Live cable connector

## Compatible Receivers



vLoc3-Pro



vLoc3-9800



vLoc3-ML



vLoc2 receiver series



VM-510FFL+

Local Vivax-Metrotech Distributor:



**INTEC MARKETING SERVICES SDN BHD**

LOT 8678, PENDING COMMERCIAL CENTRE  
JALAN PENDING, KUCHING  
93450, SARAWAK, MALAYSIA

P: +60 82 344 596  
E: sales@intec.com.my  
W: www.intec.com.my

**Vivax-Metrotech Corporation**

3251 Olcott Street, Santa Clara, CA 95054, USA

**T/Free: 800-446-3392**

**Tel: +1-408-734-1400**

www.vivax-metrotech.com

CONNECT WITH US ON SOCIAL MEDIA



V1.2

Please visit our website for full product specifications.

www.vivax-metrotech.com | www.vxmt.com